

CLAIMS

What is claimed is:

1. A method of calibrating a voltage controlled oscillator,
5 comprising:
 comparing a frequency of an output of a first voltage
 controlled oscillator to a reference frequency;
 accumulating a first digital value relating to a difference in
 frequency between said output of said first voltage controlled oscillator
10 and said reference frequency; and
 controlling a frequency of said output of said first voltage
 controlled oscillator based on said accumulated first digital value.
2. The method of calibrating a voltage controlled oscillator
15 according to claim 1, further comprising:
 converting said accumulated first digital value into a first
 analog signal for control of said first voltage controlled oscillator.
3. The method of calibrating a voltage controlled oscillator
20 according to claim 1, further comprising:
 scanning said accumulated first digital value into a built-in
 self test (BIST) path.

4. The method of calibrating a voltage controlled oscillator according to claim 1, further comprising:

comparing a frequency of an output of a second voltage controlled oscillator to said reference frequency;

5 accumulating a second digital value relating to a difference in frequency between said output of said second voltage controlled oscillator and said reference frequency; and

controlling a frequency of said output of said second voltage controlled oscillator based on said accumulated second digital value.

10

5. The method of calibrating a voltage controlled oscillator according to claim 4, further comprising:

comparing a frequency of an output of a third voltage controlled oscillator to said reference frequency;

15 accumulating a third digital value relating to a difference in frequency between said output of said third voltage controlled oscillator and said reference frequency; and

controlling a frequency of said output of said third voltage controlled oscillator based on said accumulated third digital value.

20

6. The method of calibrating a voltage controlled oscillator according to claim 5, further comprising:

comparing a frequency of an output of a fourth voltage controlled oscillator to said reference frequency;

25 accumulating a fourth digital value relating to a difference in frequency between said output of said fourth voltage controlled oscillator and said reference frequency; and

controlling a frequency of said output of said fourth voltage controlled oscillator based on said accumulated fourth digital value.

30

7. The method of calibrating a voltage controlled oscillator according to claim 6, further comprising:

scanning each of said first digital value, said second digital value, said third digital value, and said fourth digital value into a built-in self test (BIST) path.

8. A method of calibrating a voltage controlled oscillator in a clock and data recovery (CDR) circuit, comprising:

selecting a calibration mode for at least one voltage controlled oscillator in said CDR circuit, while another voltage controlled oscillator is in an operational mode;

comparing a frequency of an output of said at least one voltage controlled oscillator to a reference frequency;

accumulating a digital value relating to a difference in frequency between said output of said at least one voltage controlled oscillator and said reference frequency; and

controlling a frequency of said output of said at least one voltage controlled oscillator based on said accumulated digital value.

9. The method of calibrating a voltage controlled oscillator in a clock and data recovery (CDR) circuit according to claim 8, further comprising:

converting said accumulated digital value into an analog signal for control of said at least one voltage controlled oscillator.

10. The method of calibrating a voltage controlled oscillator in a clock and data recovery (CDR) circuit according to claim 8, further comprising:

scanning said accumulated digital value into a built-in self test (BIST) path.

11. A clock and data recovery circuit, comprising:
- a plurality of voltage controlled oscillators, each adapted for synchronization with a received data stream;
 - a state machine to select a calibration mode for any of said plurality of voltage controlled oscillators;
 - a frequency locked loop to compare a frequency output from any of said plurality of voltage controlled oscillators to a reference frequency; and
 - an accumulator receiving an output from said frequency locked loop, an output of which controls a frequency output from any one of said plurality of voltage controlled oscillators to within a desired tolerance of said reference frequency.
12. The clock and data recovery circuit according to claim 11, further comprising:
- a data sampler adapted to extract data from said received data stream.
13. The clock and data recovery circuit according to claim 11, wherein:
- said accumulator is a digital accumulator.
14. The clock and data recovery circuit according to claim 13, further comprising:
- a digital-to-analog converter (DAC) to convert an output of said digital accumulator into an analog frequency control signal for control of a given one of said plurality of voltage controlled oscillators.

15. The clock and data recovery circuit according to claim 13, further comprising:

5 a plurality of digital-to-analog converters (DACs) to convert an output of said digital accumulator into a respective analog frequency control signal for control of respective ones of said plurality of voltage controlled oscillators.

16. An integrated circuit including a clock and data recovery circuit, comprising:

10 a plurality of voltage controlled oscillators, each adapted for synchronization with a received data stream;

a state machine to select a calibration mode for any of said plurality of voltage controlled oscillators;

15 a frequency locked loop to compare a frequency output from any of said plurality of voltage controlled oscillators to a reference frequency; and

20 an accumulator receiving an output from said frequency locked loop, an output of which controls a frequency output from any one of said plurality of voltage controlled oscillators to within a desired tolerance of said reference frequency.

17. The integrated circuit including a clock and data recovery circuit according to claim 16, further comprising:

25 a data sampler adapted to extract data from said received data stream.

18. The integrated circuit including a clock and data recovery circuit according to claim 16, wherein:

30 said accumulator is a digital accumulator.

19. The integrated circuit including a clock and data recovery circuit according to claim 18, further comprising:

5 a digital-to-analog converter (DAC) to convert an output of said digital accumulator into an analog frequency control signal for control of a given one of said plurality of voltage controlled oscillators.

20. The integrated circuit including a clock and data recovery circuit according to claim 18, further comprising:

10 a plurality of digital-to-analog converters (DACs) to convert an output of said digital accumulator into a respective analog frequency control signal for control of respective ones of said plurality of voltage controlled oscillators.

15